

OMNI-400

OMNI-400 4-8 Zone Control/Communicator

CE



Designed for quick and easy installation, the OMNI-400 is ideal for the home, apartment or office. The fully featured OMNI-400 offers many standard features such as 8 fully programmable zones, 15 user codes, built-in telephone line monitor, 128 event log, four totally programmable trigger outputs, up to 10 relays, and much more. For price and performance, it's the best control panel in its class.

control communicator

The OMNI-400 offers more features and options than any other in its class. Experience the value with FBI's new OMNI Series.

Features:


- ◆ Unattended downloading
- ◆ 4-8 fully programmable zones
- ◆ 128 event history with time and date stamp
- ◆ Auto arming options based on AC real time clock
- ◆ 15 user codes
- ◆ Built-in telephone line monitor
- ◆ 4 programmable trigger outputs
- ◆ Up to 10 relays
- ◆ 2 fully programmable entry timers
- ◆ SIA false alarm reduction features
- ◆ Bell supervision
- ◆ Temporal bell standard for fire

PERIPHERALS



CE

CE2R
Wireless Remote-Control Keyfob



TAM-1
Telephone Access Module

CE



Chatbak-V
Verbal Status Module

- Stand-alone or place next to any FBI keypad
- Gives system status of your alarm in easy-to-understand English
- One button arming station in Home or Away modes
- Family/office message center
- Verbal chime mode

OMNI-400



OMNI-KP



OMNI-LCD



XK-108

SYSTEM COMPONENTS:

OMNI-400LT: Includes Control/Communicator. Transformer and Keypads available separately

OMNI-400: Includes Control/Communicator and 16.5V 25VA Transformer

OMNI-400X: PC Board only

OMNI-KP: Fixed word LCD keypad. Available in English, French, Italian, Spanish, Dutch, Chinese, Hebrew and Portuguese

OMNI-LCD: Custom language LCD keypad

XK-108: 8 zone LED keypad, surface mount, individual LEDs for zones and system status

CE2R: Wireless remote control keyfob

TAM-1: Telephone access module

Chatbak-V: Verbal status module

SPECIFICATIONS:

Zones:

- ◆ 4 fully programmable zones (8 zones with our unique zone doubling option), each selectable for EOL supervision, NO or NC devices
- ◆ Four emergency keypad conditions (fire, panic, aux, duress)
- ◆ Versatile zone types:
Controlled zone types include; Instant, exit/entry, interior, day, and keyswitch, with options for fast loop response, restore and chime by zone. 24 hour zone types include: fire, burglary, silent, trouble, medical
- ◆ Programmable central station reporting codes per zone
- ◆ Smoke reset and verification features
- ◆ Cross zone capabilities
- ◆ New stay delay zone type

Additional Features:

- ◆ Cancel code feature
- ◆ Installer walk test feature
- ◆ Real time clock with reminder when time needs to be reset
- ◆ Chime on/off feature through keypad
- ◆ Keypad tamper function with optional CS transmission
- ◆ Swinger shutdown option
- ◆ System stabilization time prevents false alarms during powerup
- ◆ NFPA temporal bell
- ◆ Arm while faulted
- ◆ Supervised bell output
- ◆ 128 Event Log
- ◆ Paging format, follow me (domestic dialing)

User Codes:

- ◆ 15 user codes
- ◆ Ambush and door strike codes
- ◆ Open/close by user ID
- ◆ Unique O/C codes for all users

Programming/Remote Operations:

- ◆ Remote commands include: arm, disarm, bypass zones, change user codes, read system status
- ◆ Remote operations can be performed through PC Downloader
- ◆ Upload/download remote operations of all system features and functions. ALL ON A SINGLE CALL. With FBIII Answering Machine Bypass

- ◆ Remote and/or unattended downloading
- ◆ On-site programming directly through keypad (LED or LCD)
- ◆ CSID and installer code, anti-takeover feature

Keypads:

- ◆ Supports up to 8 keypads per system (LED, Fixed word LCD, and custom language programmable LCD)
- ◆ LED keypad displays status of each individual zone, with indications of Alarm, Trouble, Tamper, Stay, Bypass, Instant, Power and Not Ready conditions
- ◆ Fixed word LCD keypad displays status of each zone, with indications of Alarm, Fire, Trouble, Tamper, Bypass, Page, RF Supervision, Canceled, Chime, Phone, Test, AC, Battery, and Not Ready conditions
- ◆ English language LCD keypads display complete system status, in 2 line by 16 character Supertwist™ display for easy viewing
- ◆ Most keypads available in many languages. Please contact your nearest distributor for details.

Central Station Communications:

- ◆ Two CS account numbers (3 or 4 digits)
- ◆ Pulse formats include: 3x1, 4x1, 4x2, Expanded: Speeds 10, 20, 40PPS with or without parity
- ◆ FBI Superfast, ADEMCO Express 4x1 and 4x2 Formats, ADEMCO CID Format
- ◆ Split and dual reporting option for openings and closings
- ◆ Test options include daily, weekly, 27, 60 or 90 day, hourly intervals test by time, event

Power Specifications:

- ◆ Watchdog circuitry ensures integrity of microprocessor
- ◆ Total aux. power: 500 mA. regulated
- ◆ Transformer: 16.5V 25VA

Listings:*

- ◆ Residential UL Household Combination Burglary/Fire
- ◆ UL Mercantile Burglary Listing: Local Grade A, Police Connect Grade A, Grade AA
- ◆ California State Fire Marshal (CSFM)
- ◆ CE, TBR21, Austel

*Listing pending as of printing date